



# MAXETA

Postboks 177 Sentrum 3701 Sikken  
Tlf. 35 91 40 00 - Fax 35 91 40 10  
maxeta@maxeta.no - www.maxeta.no

## Elforsyning og jernbane

### Presskabelsko, Cu, ufortinnet



#### Cu-presskabelsko ufortinnet for kobberledere \*rm-\*sm DIN 46235

##### Andre hulldiametere på forespørsel

\*rm = rund mangetrådet

\*sm = sektor mangetrådet

Elnr	Varenr	Tverrsnitt mm <sup>2</sup>	Bakke K.nr.	Lask- hull mm Ø	Lengde til senter lask hull	Lask- bredde mm
	300001001	10	6	6,5	27,5	8,5
2088360	300002002	16	8	6,5	35	12
2088364	300002003	16	8	8,4	35	12
2088368	300004004	16	8	10,5	37	17
2088370	300004005	16	8	13	37	19
	300006006	25	10	6,5	39	15
2088384	300006007	25	10	8,4	39	15
2088388	300008008	25	10	10,5	39	17
2088390	300008009	25	10	13	39	19
	300010010	35	12	8,4	42	17
2088418	300010011	35	12	10,5	42	19
2088420	300012012	35	12	13	42	21
2088430	300013013	50	14	8,4	51	22
2088434	300013014	50	14	10,5	51	22
2088438	300013015	50	14	13	51	22
2088440	300016016	50	14	17	51	28
2088454	300017017	70	16	10,5	54	24
2088458	300017018	70	16	13	54	24
	300019019	70	16	17	54	32
2088470	300021021	95	18	10,5	64	28
2088474	300021022	95	18	13	64	28
	300023023	95	18	17	67	32
	300025359	120	20	10,5	69	32
2088494	300025025	120	20	13	69	32
2088498	300025026	120	20	17	69	32
2088510	300028028	150	22	13	77	34
	300028029	150	22	17	77	34
2088530	300031031	185	25	13	81	37
2088546	300034034	240	28	13	91	42
2088550	300034035	240	28	17	91	42
2088566	300037037	300	32	17	100	48
2088586	300039039	400	38	17	115	55