



MAXETA

Postboks 177 Sentrum 3701 Skien
Tlf. 35 91 40 00 - Fax 35 91 40 10
maxeta@maxeta.no - www.maxeta.no

Elforsyning og jernbane Loopklemmer, Al



Al-loopklemmer DIN 48075

For Al- og Feral-linjer med lik diameter

Materiale:

Klemmekropp: høyverdig Al-legering AlMgSi1F32 eller GAlSi12
Skruer og muttere: stål A2-80

NV = nøkkelvidde

Elnr	Varenr	Al line diameter mm Ø	Antall skruer	Skrue-dim. NV	Tiltr.-moment Nm
2871903	440030239	10,3 - 12,5	2	17	38
2871904	440031732	12,6 - 14,9	2	17	38
2871905	440032160	15,0 - 17,1	3	17	38
2871906	440033733	17,2 - 19,0	3	19	65
2871907	440034734	19,1 - 21,0	3	19	65
2871908	440035063	21,1 - 23,4	3	19	65
2871909	440036735	23,5 - 25,7	3	19	65
2871910	440037463	25,8 - 27,8	3	19	65
2871911	440038658	27,9 - 29,9	3	19	65
	440039052	29,0 - 31,9	3	19	65
	440041065	32,5 - 33,4	3	19	65
	449067001	35,2 - 37,0	3	19	65
2871915	440044244	36,9 - 42,0	3	19	65